

STANDARD TYPES
OF

Prest-O-Lite

STARTING, LIGHTING
AND IGNITION
BATTERIES

—
Eastern Prices

~~*Pacific Coast Prices*~~

January 15, 1919

Subject to change without notice

—

BECKMAN ELECTRIC CO.

124 S. Central Avenue

Lima, Ohio

L. E. Ruffe
Add Ohio

Manufactured by

The Prest-O-Lite Co., Inc.

*The Oldest Service to Automobile
Owners in America*

Standard Types of Prest-O-Lite Starting, Lighting and Ignition Batteries

6-VOLT LIGHTING AND IGNITION TYPES

(Ratings are given as a guide to the user to indicate how often the battery should be charged if the car is not equipped with a generator. These ratings are based on continuous discharge. Intermittent discharge will add 30 per cent. to these ratings.)

TYPE	Price		Hours Continuous Discharge at Rate of			Charging Rates		Outside Dimensions Add 1/4 inch to length to determine length over handles			Weight (Pounds)
	Sale	Exch. †	5 amps.	7 1/2 amps.	10 amps.	Starting Rate	Finishing Rate	Length (Inches)	Width (Inches)	Height Over All Including Handles (Inches)	
65AHL 65WHNL	\$17.90 17.90	\$16.85 16.85	5 5	3 3	2.2 2.2	4 amps. 4 "	2 amps. 2 "	5 1/4 5 1/4	7 1/4 7 1/4	10 3/4 8 3/4	22 22
67AHL 67WHNL	21.45 21.45	20.15 20.15	7.5 7.5	4.5 4.5	3 3	6 amps. 6 "	3 amps. 3 "	6 3/4 6 3/4	5 1/4 7 1/4	10 3/4 8 3/4	27 27
67WHP 67WHNL	21.45 21.45	20.15 20.15	7.5 7.5	4.5 4.5	3 3	6 "	3 "	6 3/4 6 3/4	7 1/4 7 1/4	8 3/4 8 3/4	27 27
69AHL 69WHNL	24.00 24.00	22.55 22.55	10.8 10.8	6.5 6.5	4.5 4.5	8 amps. 8 "	4 amps. 4 "	7 1/4 7 1/4	5 1/4 7 1/4	10 3/4 8 3/4	36 36
611AHL 611WHNL	27.35 27.35	25.70 25.70	14 14	8.5 8.5	6 6	10 amps. 10 "	5 amps. 5 "	9 1/4 9 1/4	5 1/4 7 1/4	10 3/4 8 3/4	42 42
613AHL 613WHNL	30.35 30.35	28.55 28.55	17 17	10.75 10.75	7.5 7.5	12 amps. 12 "	6 amps. 6 "	10 1/4 10 1/4	5 1/4 7 1/4	10 3/4 8 3/4	50 50
615AHL 615WHNL	35.10 35.10	33.00 33.00	20.5 20.5	13 13	9 9	14 amps. 14 "	7 amps. 7 "	11 1/4 11 1/4	5 1/4 7 1/4	10 3/4 8 3/4	53 53
619AHL 619WHNL	39.65 39.65	37.25 37.25	27 27	17.5 17.5	12.5 12.5	18 amps. 18 "	9 amps. 9 "	14 1/4 14 1/4	5 1/4 7 1/4	10 3/4 8 3/4	66 66

†Exchange Price: Price applying when old battery of similar size is turned in as part payment.

How to Order a Prest-O-Lite Battery for Your Car

If you have been using some other make of battery, and are not positive which style of Prest-O-Lite Battery should be ordered to take its place, tell us the make, year and model of your car. With this information we will have no trouble in supplying a Prest-O-Lite Battery of the correct size for your car.

If the battery is to be used for the operation of any electrical device, in other than automobile service, state make and character of the service, the voltage, current consumption and the number of hours service desired.

Styles of Terminals

We furnish several different styles of terminals—burned-on terminals, taper-pin terminals and clamp terminals.

Unless otherwise specified, we shall supply the type that seems necessary, according to our record of the kind used by the maker of your car.

All lighting batteries are supplied with bolt and nut type terminals to which the wiring on any car or electrical device is easily fastened.

We are not liable for damage to goods in transit. Our responsibility ceases when we deliver batteries in good condition to the transportation company. When damage occurs, so indicate on the carrier's receipt before signing and file claim with the transportation company after the extent of the damage has been determined.

STANDARD TYPES

OF

Prest-O-Lite

STARTING, LIGHTING AND IGNITION BATTERIES

Eastern Prices

~~Per Unit Price~~

January 15, 1919

Subject to change without notice

BECKMAN ELECTRIC CO.

124 S. Central Avenue

Lima, Ohio

L.E. Ruffer
Adm. Ohio

Manufactured by

The Prest-O-Lite Co., Inc.

The Oldest Service to Automobile
Owners in America

Standard Types of Prest-O-Lite Starting, Lighting and Ignition Batteries

STARTING TYPES

TYPE	Price		Hours Continuous Discharge at Rate of			Amps. for 20 Mins.	Charging Rates		Outside Dimensions Add $\frac{1}{8}$ inch to length to determine length over handles			Weight (Pounds)
	Sale	Exch. †	5 amps.	7½ amps.	10 amps.		Starting Rate	Finishing Rate	Length (Inches)	Width (Inches)	Height Over All Including Handles (Inches)	
6-Volt												
611AH7	\$32.65	\$30.05	14	8.5	6	85	10 amps.	5 amps.	8½	6½	10	42
611WHN	32.65	30.05	14	8.5	6	85	10 "	5 "	8½	7½	8½	41
611RHN	36.45	33.55	17	10	7.4	100	12 "	6 "	8½	7½	9¼	45
611RHNS	36.45	33.55	17	10	7.4	100	12 "	6 "	8½	7½	9¼	45
611RHN2	36.45	33.55	17	10	7.4	100	12 "	6 "	19½	3½	9¼	45
611BHN	43.20	39.75	22	14	10	125	15 "	7.5 "	8½	7½	11½	59
613AH	37.10	34.15	17	10.75	7.5	102	12 amps.	6 amps.	10½	5½	10	50
613AH2	37.10	34.15	17	10.75	7.5	102	12 "	6 "	14½	4½	10	50
613WHN	37.10	34.15	17	10.75	7.5	102	12 "	6 "	10½	7½	8½	48
613WHN2	37.10	34.15	17	10.75	7.5	102	12 "	6 "	19½	4½	8½	48
613RHN	40.90	37.65	21	13	9.3	120	14 "	7 "	10½	7½	9¼	51
613RHN2	40.90	37.65	21	13	9.3	120	14 "	7 "	19½	4½	9¼	51
613RHN7	40.90	37.65	21	13	9.3	120	14 "	7 "	10½	7½	9¼	51
613JFN	36.45	33.55	18	11.5	8	105	12 "	6 "	8½	7½	9¼	44
613BHN	48.55	44.65	27	17	12	152	18 "	9 "	10½	7½	10½	64
613BHN7	48.55	44.65	27	17	12	152	18 "	9 "	10½	7½	10½	64
613CM2	65.20	60.00	24	15	11	140	16 "	8 "	17½	5½	11½	89
615AH	39.65	36.50	20.5	13	9	119	14 amps.	7 amps.	11½	5½	10	53
615AH2	39.65	36.50	20.5	13	9	119	14 "	7 "	14½	4½	10	53
615WHN	39.65	36.50	20.5	13	9	119	14 "	7 "	11½	7½	8½	51
615WHN2	39.65	36.50	20.5	13	9	119	14 "	7 "	19½	4½	8½	51
615RHN	46.20	42.50	25	15	11.4	140	16 "	8 "	11½	7½	9¼	62
615RHN2	46.20	42.50	25	15	11.4	140	16 "	8 "	19½	4½	9¼	62
615JFN	39.65	36.50	22	14	10	125	14 "	7 "	10	7½	9¼	50
615JFN2	39.65	36.50	22	14	10	125	14 "	7 "	19½	4½	9¼	50
615BHN	56.20	51.70	32	20	15	177	20 "	10 "	11½	7½	11½	75
619AH	48.55	44.65	27	17.5	12.5	153	18 amps.	9 amps.	14½	5½	10	66
619WHN	48.55	44.65	27	17.5	12.5	153	18 "	9 "	14½	7½	8½	64
619RHN	56.90	52.35	33	21	15	180	20 "	10 "	14½	7½	9¼	75
619RHN2	56.90	52.35	33	21	15	180	20 "	10 "	19½	5½	9¼	75
619JFN7	49.90	45.90	30	19	13	170	18 "	9 "	10½	8½	9¼	62
8-Volt												
89RHN	43.10	39.65	13.2	8	5.6	80	10 amps.	5 amps.	10½	7½	9¼	50
10-Volt												
107RHN	43.80	40.30	9.5	5.8	4	60	7 amps.	3.5 amps.	9½	7½	9¼	48
12-Volt												
127WMN	45.20	41.60	7.5	4.5	3	51	6 amps.	3 amps.	11½	7½	8½	55
127WHN	45.20	41.60	7.5	4.5	3	51	6 "	3 "	11½	7½	8½	55
127RHN	45.65	41.95	9.5	5.8	4	60	7 "	3.5 "	12½	7½	9¼	58
127RHN4	45.65	41.95	9.5	5.8	4	60	7 "	3.5 "	13½	6½	9¼	58
129WHN	52.65	48.45	10.8	6.5	4.5	68	8 amps.	4 amps.	13½	7½	8½	64
129WHN3	52.65	48.45	10.8	6.5	4.5	68	8 "	4 "	19½	5½	8½	64
129RHN	58.80	54.10	13.2	8	5.6	80	10 "	5 "	13½	7½	9¼	74
129RHN3	58.80	54.10	13.2	8	5.6	80	10 "	5 "	19½	5½	9¼	74
129JFN	52.25	48.10	11	7	5	70	7 "	3.5 "	12½	7½	9¼	62
1211AH	61.10	56.20	14	8.5	6	85	10 amps.	5 amps.	17½	5½	10	80
1211WHN	61.10	56.20	14	8.5	6	85	10 "	5 "	16½	7½	8½	78
1211RHN	68.00	62.55	17	10	7.4	100	12 "	6 "	16½	7½	9¼	89
1211RHN3	68.00	62.55	17	10	7.4	100	12 "	6 "	19½	6½	9¼	89
1213AH	68.35	62.90	17	10.75	7.5	102	12 amps.	6 amps.	20½	5½	10	98
1213WHN	68.35	62.90	17	10.75	7.5	102	12 "	6 "	19½	7½	8½	95
1215AH3	76.90	70.75	20.5	13	9	119	14 amps.	7 amps.	14½	8½	10	110
16-Volt												
167WHN	60.10	55.30	7.5	4.5	3	51	6 amps.	3 amps.	14½	7½	8½	73
169WHN	68.00	62.55	10.8	6.5	4.5	68	8 "	4 "	18½	7½	8½	88
18-Volt												
187AH5	65.20	60.00	7.5	4.5	3	51	6 amps.	3 amps.	14½	6½	10	85
187RHN7	70.35	64.70	9.5	5.8	4	60	7 "	3.5 "	15½	7½	9¼	87
189AH5	79.20	72.85	10.8	6.5	4.5	68	8 amps.	4 amps.	14½	8	10	100
189RHN7	86.00	79.00	13.2	8	5.6	80	10 "	5 "	15½	9½	9¼	110
24-Volt												
243GM6	63.65	58.55	2	1.2	.8	17	2.5 amps.	1.25 amps.	11½	8½	9½	73
247AH5	81.80	75.25	7.5	4.5	3	51	6 amps.	3 amps.	19½	6½	10	110
30-Volt												
305WHN	79.20	72.85	5	3	2.2	34	4 amps.	2 amps.	20½	7½	8½	110

† Exchange Price: Price applying when old battery of similar size is turned in as part payment.

FOR LIGHTING AND IGNITION TYPES SEE REVERSE SIDE